

FOCUSRITE USA FUSE CHART (USA ONLY)

Focusrite Model	External 1	External 2	Internal 1	Internal 2	Internal 3
PLATINUM					
VoiceMaster	T315mA	none	none	none	none
ToneFactory	T315mA	none	none	none	none
Compounder	T315mA	none	none	none	none
MixMaster	T630mA	none	none	none	none
Penta	T315mA	none	none	none	none
Trak Master	T315mA	none	none	none	none
RED Series					
Red 1	none	none	T250mA	T250mA	none
Red 2	none	none	T250mA	T250mA	none
Red 3	none	none	T315mA *	T315mA *	none
Red 4	none	none	T250mA	T250mA	none
Red 5	T10A	none	T6.3A	none	none
Red 6	none	none	T250mA	T250mA	none
Red 7	none	none	T250mA	T250mA	none
Red 8	none	none	T250mA	T250mA	none
BLUE Series					
Blue 230	none	none	T250mA	T250mA	none
Blue 245	T500mA	none	T250mA	T250mA	T1.6A
Blue 260	T500mA	none	T250mA	T250mA	T500mA
Blue 300	none	none	T315mA	T315mA	none
Blue 315	none	none	T250mA	T250mA	none
Blue 330	none	none	T250mA	T250mA	none
Green Series					
Green 1	none	none	T315mA	none	none
Green 2	none	none	T315mA	none	none
Green 3	none	none	T315mA	none	none
Green 4	none	none	T500mA *	none	none
Green 5	none	none	T315mA	none	none
Green 6	none	none	T500mA *	none	none
ISA Series					
ISA 110 module	none	none	none	none	none
ISA 85109 module	none	none	none	none	none
ISA 85110 module	none	none	none	none	none
ISA 110 L E	T315mA	none	T500mA	none	none
ISA 115 HD	none	none	none	none	none
ISA 115 L40	none	none	none	none	none
PSU 120	T1.6A	none	none	none	none
PSU 121	Superceded by PSU 121H				
PSU 121H	T1.6A	none	T6.3A	T6.3A	none
PSU 122	T1.6A	none	none	none	none
ISA 130 module	none	none	none	none	none
ISA 131	T500mA	T500mA	none	none	none
ISA 215	T250mA	T250mA	none	none	none
ISA 220 S Pack	T630mA	none	none	none	none
ISA 430 P Pack	T1.6mA	none	none	none	none

NOTES:

- 1) All fuses are 5 X 20 MM metric type fuse.
- 2) All fuses are Time Lag (Slo-Blow) fuses.
- 3) Fuse values marked * are recommended by TRD

Chart courtesy of
Thermal Relief Design, Inc.
Las Vegas, NV
January, 2002